





SIRIUS 3RT10 3-Pole with AC Coil

Ordering Information	Coil Voltage Codes**		
3RT101* through 3RT104* ▶ 4-point AC coil can be wired on top, bottom, or diagonally. ▶ Direct mount 3RU11 or 3RB10 solid state overload relays to create starters. ▶ Snap-on auxiliary contacts, surge suppressors, and timers. ▶ Front and side mounted auxiliary contacts from sizes 3RT102 through 3RT104 ▶ For overload relays see page 19. ▶ For accessories, replacement parts, technical data, and dimensions see Siemens Industrial Control Products Catalog - CPPC-06000.	ACV 60Hz	ACV 50Hz	Code
	24 120 208 240 277 480 600	24 110 208 220 ë ë ë	C2 K6 M2 P6 U6 V6 T6
Replace the ** in the contactor catalog number with a coil code from the table above.			

Illustration	Enclosed Amp Ratings		Single-Phase HP Ratings		Three-Phase HP Ratings				Auxiliary Contacts		Screw Terminals		Cage Clamp Terminals	
	AC-3	AC-1	115V	230V	200V	230V	460V	575V	NO	NC	Catalog No.	Price \$	Catalog No.	Price \$
 3RT101	3RT101													
	7	18	1/4	3/4	1 1/2	2	3	5	1	ë	3RT1015-1A**1	55.	3RT1015-2A**1	60.
									ë	1	3RT1015-1A**2		3RT1015-2A**2	
	9	22	1/3	1	2	3	5	7 1/2	1	ë	3RT1016-1A**1	72.	3RT1016-2A**1	77.
									ë	1	3RT1016-1A**2		3RT1016-2A**2	
	12	22	1/2	2	3	3	7 1/2	10	1	ë	3RT1017-1A**1	89.	3RT1017-2A**1	94.
								ë	1	3RT1017-1A**2	3RT1017-2A**2			
 3RT102	3RT102													
	9	40	1/3	1	2	3	5	7 1/2	ë	ë	3RT1023-1A**0	81.	3RT1023-3A**0	84.
	12	40	1/2	2	3	3	7 1/2	10	ë	ë	3RT1024-1A**0	105.	3RT1024-3A**0	108.
	17	40	1	3	5	5	10	15	ë	ë	3RT1025-1A**0	121.	3RT1025-3A**0	124.
 3RT103	3RT103													
	25	40	2	3	7 1/2	7 1/2	15	20	ë	ë	3RT1026-1A**0	136.	3RT1026-3A**0	139.
	28	50	2	5	7 1/2	10	20	25	ë	ë	3RT1033-1A**0	156.	3RT1033-3A**0	159.
 3RT104	3RT104													
	32	50	2	5	10	10	25	30	ë	ë	3RT1034-1A**0	172.	3RT1034-3A**0	175.
	40	50	3	7 1/2	10	15	30	40	ë	ë	3RT1035-1A**0	191.	3RT1035-3A**0	194.
	3RT104													
	50	55	3	10	15	15	40	50	ë	ë	3RT1036-1A**0	206.	3RT1036-3A**0	209.
	65	100	5	15	20	25	50	60	ë	ë	3RT1044-1A**0	291.	3RT1044-3A**0	294.
	3RT104													
	80	120	7 1/2	15	25	30	60	75	ë	ë	3RT1045-1A**0	331.	3RT1045-3A**0	334.
	95	120	10	ë	30	30	75	100	ë	ë	3RT1046-1A**0	453.	3RT1046-3A**0	456.

⌘ For 3RT101 use B0.